

MOSA

Электростанции GE 11000 HBS/GS



Архангельск (8182)63-90-72
Астана +7(7172)727-132
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Казань (843)206-01-48

Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41

Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78

Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

Единый адрес для всех регионов: mzs@nt-rt.ru || www.mosa.nt-rt.ru

GENERATING SET GE 11000 HBS/GS

- Honda OHV petrol engine
- Engine shut down for low level oil
- Single-phase synchronous alternator
- Output sockets : 1 x 230V 32A 2P+T CEE
1 x 230V 16A 2P+T CEE - 1 x 230V 16A 2P+T Schuko
- GFI - ELCB (Ground Fault Interruptor)
- Circuit breaker
- Wrap around protective frame
- Meets EC directives



Standard equipment	Petrol engine	Air cooling	Electric starter	Battery 12V	Hour meter	Oil alert	Engine shut down (oil)			
Options on request	Synchronous alternator	Sockets	ELCB-GFI	Circuit Breaker	Thermal shut off	Voltmeter				
	● 230V plugs				● Earthing kit			● Trolley CTM10		

Technical data

GE 11000 HBS/GS

A.C GENERATION – 50 Hz	Single-phase synchronous alternator, self-excited, self-regulated, brushless
* Stand-by single-phase power	11 kVA (9.9 kW) / 230 V / 47.8 A
* PRP single-phase power	10 kVA (9 kW) / 230 V / 43.5 A
cos φ	0.9
Insulation class	H
* Output powers according to ISO 8528-1	
ENGINE	4-stroke petrol, air cooled, OHV
Model	Honda GX 630
* Stand-By net power	14.5 kW (19.7 HP)
* PRP net power	10.5 kW (14.3 HP)
Cylinders/ Displacement	2/ 688 cm ³
Speed	3000 rpm
Fuel consumption (75% of PRP)	3.9 l/h
* Powers according to SAE J1349	
GENERAL SPECIFICATION	
Tank capacity	18.1 l
Running time (75% of PRP)	4.5 h
IP protection degree	IP 23
*Dimensions LxWxh (mm)	935x525x645
*Dry weight	145 kg
**Acoustic power LwA (pressure LpA)	99 dB(A)(74 dB(A) @ 7m)
* Dimensions and weight without trolley/trailer. ** For indoor use / For fixed installation only, in compliance with Directive 2000/14/EC	

Архангельск (8182)63-90-72
Астана +7(7172)727-132
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Казань (843)206-01-48

Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41

Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78

Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

Единый адрес для всех регионов: mzs@nt-rt.ru || www.mosa.nt-rt.ru

