

MOSA

Электростанции GE 2500 SR FAMILY



Архангельск (8182)63-90-72
Астана +7(7172)727-132
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Казань (843)206-01-48

Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41

Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78

Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

Единый адрес для всех регионов: mzs@nt-rt.ru || www.mosa.nt-rt.ru

GENERATING SET GE 2500 SR FAMILY

- SUBARU-ROBIN OHC petrol engine
- Engine shut down for low oil level
- Single-Phase synchronous alternator
- Output sockets: 2 x 230V 16A 2P+T SCHUKO
- Overload thermal shut off
- Battery charger with fuse protection
- Protective frame
- Silenced
- Portable
- Meets EC directives for safety and noise level



Standard equipment											
	Petrol engine	Air cooling	Manual recoil	Oil alert	Engine shut down (oil)						
	Synchronous alternator	Sockets	Thermal shut off	Battery charger							

Options on request

● 230V Plug

● Earthing kit

Technical data

GE 2500 SR FAMILY

A.C. GENERATION - 50 Hz

Single-phase synchronous alternator, self-excited, self-regulated, brushless

* Stand-by single-phase power

2.3 kVA / 230V / 10 A

* PRP single-phase power

2 kVA / 230V / 8.7 A

Cos φ

1

Battery charger

12V d.c. / 10A

Insulation class

H

* Output powers according to ISO 8528-1

ENGINE

4-stroke petrol, air cooled, OHC

Model

SUBARU EX 17

* Stand-By net power

2.9 kW (3.9 HP)

* PRP net power

2.6 kW (3.5 HP)

Cylinders/ Displacement

1/ 169 cm³

Speed

3000 rpm

Fuel consumption (75% of PRP)

0.95 l/h

* Powers according to SAE J1349

GENERAL SPECIFICATIONS

Tank capacity

3.6 l

Running time (75% of PRP)

3.8 h

IP protection degree

IP 23

Dimensions LxWxh (mm)

555x370x390 mm

Dry weight

30 kg

*Measured acoustic power LwA (pressure LpA)

95 dB(A)(70 dB(A) @ 7m)

*Guaranteed acoustic power LwA (pressure LpA)

95 dB(A)(70 dB(A) @ 7m)

* Acoustic power according to European Directive 2000/14/EC

Архангельск (8182)63-90-72
Астана +7(7172)727-132
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Казань (843)206-01-48

Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41

Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78

Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

Единый адрес для всех регионов: mzs@nt-rt.ru || www.mosa.nt-rt.ru

