

MOSA

Электростанции GE 10 YSXC



Архангельск (8182)63-90-72
Астана +7(7172)727-132
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Казань (843)206-01-48

Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41

Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78

Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

Единый адрес для всех регионов: mzs@nt-rt.ru || www.mosa.nt-rt.ru

GENERATING SET GE 10 YSXC

FEATURES

- Engine protection EP6
- Combined system voltage regulation: electronic AVR + Compound
- Sockets : 1x400V 16A 3P+N+T CEE - 2x230V 16A 2P+T CEE
o 1x230V 16A 2P+T SCHUKO
- ELCB-GFI (Ground Fault Interruptor)
- Circuit breaker
- Emergency stop button
- Super Silenced
- Ready for connection to automatic transfer unit EAS
- Meets EC Directives for safety and noise level



The images are for reference

Standard Equipment	Diesel engine	Water cooling	Battery 12V	Engine protection	Electric Starter	[OIL] Low press. shut down	[°C] High water shut down	[Hi H] Over speed shut down	[FUEL] Low fuel shut down	[bELt] Battery charge alarm	Central lifting eye
			Cold start aid	Remote starting	Rpm-meter	Hours-meter	Battery voltmeter	Voltmeter	Hz Frequency-meter	Ammeter	Fuel level gauge
	Synchronous alternator	AVR + COMPOUND (Automatic Voltage Regulator)	Sockets	Sockets	ELCB-GFI	Circuit breaker	Voltmeter phase selector	Emergency stop button	Local/Remote Start selector	Ready for EAS/TCM	

Options on request	• Remote control TCM35 • Automatic transfer unit (AMF) EAS 17-809	• Tank locking cap • Earthing kit	• Site tow CTL300 • Road trailer CTV4
--------------------	--	--	--

Factory installation options	• Water heater WH • Radio control
------------------------------	--

Technical data

GE 10 YSXC

A.C. GENERATION - 50 Hz - Three-phase synchronous alternator, self-excited, self-regulated, brushless

* Stand-by three-phase power	9.5 kVA (7.6 kW) / 400V / 13.7 A
* PRP three-phase power	9 kVA (7.2 kW) / 400V / 13 A
* PRP single-phase power	4.5 kVA / 230V / 19.5A
Cos φ	0.8
Insulation class	H

* Output powers according to ISO 8528-1

ENGINE - 4-stroke diesel natural aspirated, indirect injection, Water cooling

Model	YANMAR 3TNV76
* Stand-By net power	9 kW (12.2 HP)
* PRP net power	8.2 kW (11.1 HP)
Cylinders/ Displacement	3 / 1116 cm³
Speed	1500 rpm
Fuel consumption (75% of PRP)	1.8 l/h

* Powers according to ISO 3046-1

GENERAL SPECIFICATIONS

Tank capacity	30 l
Running time (75% of PRP)	16.5 h
IP protection degree	IP 23
* Dimensions LxIxD	1460x700x920 mm
* Dry weight	410 kg
** Measured acoustic power LwA (pressure LpA)	87 dB(A) (62 dB(A) @ 7m)
** Guaranteed acoustic power LwA (pressure LpA)	88 dB(A) (63 dB(A) @ 7m)

* Dimensions and weight without trolley/trailer. / ** Acoustic power according to European Directive 2000/14/EC

Архангельск (8182)63-90-72
Астана +7(7172)727-132
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Казань (843)206-01-48

Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41

Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78

Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

Единый адрес для всех регионов: mzs@nt-rt.ru || www.mosa.nt-rt.ru

