

MOSA

Электростанции GE 12000 HBS/GS



Архангельск (8182)63-90-72
Астана +7(7172)727-132
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Казань (843)206-01-48

Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41

Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78

Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

Единый адрес для всех регионов: mzs@nt-rt.ru || www.mosa.nt-rt.ru

STROOMAGGREGAAT GE 12000 HBS/GS

- Honda OHV benzinemotor
- Olieniveau beveiliging
- Driefase synchrone generator 400/230V
- Uitgang: 1x400V 32A 3P+N+T CEE - 1x230V 32A 2P+T CEE
1x230V 16A 2P+T SCHUKO
- ELCB-GFI (aardlekschakelaar)
- Circuit breaker
- Buizenframe
- 100% kwaliteit - Made in Europe



Standard Equipment	 Petrol engine	 Air cooling	 Electric Starter	 Battery 12V	 Oil pressure Indicator	 Engine shut down (oil)	 Hours-meter			
	 Synchronous alternator	 Compound	 Sockets	 Sockets	 ELCB-GFI	 Circuit breaker	 Thermal shut off	 Voltmeter		

-  Options on request
- Earthing kit
 - Hand trolley CTM10

Technical data

GE 12000 HBS/GS

A.C. GENERATION - 50 Hz - *Three-phase synchronous alternator, self-excited, self-regulated*

* Stand-by three-phase power	13 kVA (10.4 kW) / 400 V / 18.7 A
* PRP three-phase power	11.5 kVA (9.2 kW) / 400 V / 16.6 A
* PRP single-phase power	6 kVA / 230 V / 26 A
Cos φ	0.8
Insulation class	H

* Output powers according to ISO 8528-1

ENGINE - *4-stroke petrol, OHV, Air cooling*

Model	Honda GX 630
* Stand-By net power	14.5 kW (19.7 HP)
* PRP net power	10.5 kW (14.3 HP)
Cylinders/ Displacement	2/ 688 cm ³
Speed	3000 rpm
Fuel consumption (75% of PRP)	3.9 l/h

* Powers according to SAE J1349

GENERAL SPECIFICATIONS

Tank capacity	18 l
Running time (75% of PRP)	4.5 h
IP protection degree	IP 23
*Dimensions LxIxh (mm)	935x525x645
*Dry weight	142 kg
**Acoustic power LwA (pressure LpA)	99 dB(A)(74 dB(A) @ 7m)

* Dimensions and weight without trolley/trailer. / ** For fixed installation only in the EU market

Архангельск (8182)63-90-72
Астана +7(7172)727-132
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Казань (843)206-01-48

Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41

Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78

Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

Единый адрес для всех регионов: mzs@nt-rt.ru || www.mosa.nt-rt.ru

