

MOSA

Электростанции GE 14000 LD/GS EAS



Архангельск (8182)63-90-72
Астана +7(7172)727-132
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Казань (843)206-01-48

Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41

Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78

Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

Единый адрес для всех регионов: mzs@nt-rt.ru || www.mosa.nt-rt.ru

GENERATING SET GE 14000 LD/GS EAS

- Lombardini air cooled diesel engine - 3000 rpm
- Engine shut down for low pressure oil
- Electric starter
- Three phase synchronous alternator
- Output sockets : 1 x 400V 32A 3P+N+T CEE
1 x 230V 32A 2P+T CEE
1 x 230V 16A 2P+T SCHUKO
- ELCB-GFI (Ground Fault Interruptor)
- Circuit breaker
- Wrap around protective frame
- Trolley (option)
- Ready for connection to automatic transfer unit
- Meets EC directives



Standard Equipment										
	Diesel engine	Air cooling	Electric Starter	Battery 12V	Oil pressure Shut down	Battery charge indicator	Hour-meter			
Options on request										
	Synchronous alternator	Compound	Sockets 3~	Sockets 1~	ELCB-GFI	Circuit Breaker	Voltmeter	Ready for EAS/TCM	Local/remote start selector	
	● 400V plug ● 230V plug ● Earthing kit				● Automatic transfer unit (AMF) EAS 15D-806 ● Remote control			● Trolley CTM14		

Technical data

GE 14000 LD/GS EAS

A.C GENERATION – 50 Hz	Three-phase synchronous alternator, self-excited, self-regulated
* Stand-by three-phase power	15 kVA (12 kW) / 400 V / 21.7 A
* P.R.P. three-phase power	13.5 kVA (10.8 kW) / 400 V / 19.5 A
* P.R.P. single-phase power	5 kVA / 230 V / 21.7 A
Cos φ	0.8
Insulation class	H
* Output powers according to ISO 8528-1	
ENGINE	4-stroke diesel, air cooled, direct injection
Model	Lombardini 12 LD 477/2
* Stand-By net power	14.9 kW (20.3 HP)
* P.R.P. net power	13.5 kW (18.4 HP)
Cylinders/ Displacement	2/ 954 cm ³
Speed	3000 rpm
Fuel consumption (75% of P.R.P.)	2.8 l/h
* Powers according to ISO 3046-1	
GENERAL SPECIFICATION	
Tank capacity	18 l
Running time (75% of P.R.P.)	6.5 h
IP protection degree	IP 23
*Dimensions LxWxh (mm)	1000x610x750
*Dry weight	191 kg
**Acoustic power LwA (pressure LpA)	105 dB(A) (80 dB(A) @ 7 m)
* Dimensions and weight without trolley/trailer. ** For indoor use / For fixed installation only, in compliance with Directive 2000/14/EC	

Архангельск (8182)63-90-72
Астана +7(7172)727-132
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Казань (843)206-01-48

Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41

Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78

Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

Единый адрес для всех регионов: mzs@nt-rt.ru || www.mosa.nt-rt.ru

