

MOSA

Электростанции

GE 15 LSX EAS - GE 15 LSX EAS (AVR)



Архангельск (8182)63-90-72
Астана +7(7172)727-132
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Казань (843)206-01-48

Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41

Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78

Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

Единый адрес для всех регионов: mzs@nt-rt.ru || www.mosa.nt-rt.ru

GENERATING SET

GE 15 LSX EAS - GE 15 LSX EAS (AVR)

- Lombardini water cooled diesel engine - 1500 rpm
- EV engine protection
- Three-phase synchronous alternator
- Compound voltage regulation
- Output sockets : 1 x 400V 32A 3P+N+T CEE - 1 x 400V 16A 3P+T CEE
1 x 230V 32A 2P+T CEE - 1 x 230V 16A 2P+T CEE
- ELCB-GFI (Ground Fault Interruptor)
- Circuit breaker
- Super silenced
- Trailer (option)
- Ready for connection to automatic transfer unit
- Meets EC directives for safety and noise level



Standard Equipment												
	Diesel engine	Water cooling	Electric Starter	Battery 12V	Engine protection	Oil pressure shut down	High temp. water shut down	Battery charge indicator	Fuel level gauge / low fuel indicator	Hours-meter	Central lifting eye	Emergency stop button
Options on request												
	Synchronous alternator	Compound	Automatic voltage regulator *	Sockets	Sockets	ELCB-GFI	Circuit Breaker	Voltmeter phase selector	Voltmeter	Ammeter	Frequency-meter	Ready for EAS/TCM
Options on request ● 400V plug ● 230V plug ● Earthing kit ● Automatic transfer unit (AMF) EAS 28-805 ● Remote control TCM40 ● Tank locking cap ● Site tow CTL22 ● Road trolley CTV1												
Version on request ● * (AVR) Electronic voltage regulation version												

Technical Data

GE 15 LSX EAS

GE 15 LSX EAS (AVR)

A.C GENERATION – 50 Hz	Three-phase synchronous alternator, self-excited, self-regulated.	Three-phase synchronous alternator, self-excited, self-regulated, brushless
* Stand-by three-phase power	16 kVA (12.8 kW) / 400 V / 23.1 A	15 kVA (12 kW) / 400 V / 21.7 A
* P.R.P. three-phase power	15 kVA (12 kW) / 400 V / 21.7 A	13.5 kVA (10.8 kW) / 400 V / 19.5 A
P.R.P. single-phase power	5 kVA / 230 V / 21.7 A	5 kVA / 230 V / 21.7 A
Cos φ	0.8	0.8
Insulation class	H	H
* Output powers according to ISO 8528-1		
ENGINE		
4-stroke diesel, natural aspirated, indirect injection, water cooled		
Model	Lombardini LDW 1603 CHD	
* Stand-By net power	15.5 kW (21 HP)	
* P.R.P. net power	14 kW (19 HP)	
Cylinders/ Displacement	3/ 1649 cm ³	
Speed	1500 rpm	
Fuel consumption (75% of P.R.P.)	3.1 l/h	
* Powers according to ISO 3046-1		
GENERAL SPECIFICATION		
Tank capacity	60 l	
Running time (75% of P.R.P.)	19.3 h	
IP protection degree	IP 23	
*Dimensions LxWxh (mm)	1700x950x1080	
*Dry weight	540 kg	
**Measured acoustic power LwA (pressure LpA)	92 dB(A) (67 dB(A) @ 7 m)	
**Guaranteed acoustic power LwA (pressure LpA)	93 dB(A) (68 dB(A) @ 7 m)	
* Dimensions and weight without trolley/trailer. ** Acoustic power according to European Directive 2000/14/EC		

Архангельск (8182)63-90-72
Астана +7(7172)727-132
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Казань (843)206-01-48

Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41

Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78

Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

Единый адрес для всех регионов: mzs@nt-rt.ru || www.mosa.nt-rt.ru

